

UBIBOT מדריך משתמש לאפליקציית









1. **הוספת בקר**

."Add New Device" לחץ על "+" בתחתית מסך הבית, ולאחר מכן לחץ על 1.1



- 1.2 הכנס את המספר הסיריאלי של הבקר או סרוק את הברקוד.
- . 1.3 בחר את סוג הרשת ולחץ על המשך "continue", כאשר תבחר ב SIM, וודא תחילה שהסים מוכנס בצורה תקינה ומזוהה ע"י הבקר.

ul ≎ ∎	, ,	10:40 7	? ∎		10:40
evice X	Add/Setup De		×	Add/Setup Device	
ID and enter the ord: d. Please confirm GHz WiFi only. oning function of no WiFi SSID is data can boost the on after setup	e confirm the WiFi SSI correct passwo z. WiFi is not supporte are connecting to 2.4C passe enable the Positic rmobile phone when n detected. ching off the mobile d up. You can switch it a successful. 87GS1	Please ((1) 5GHz you an (2) Pleas your m (3) Switch setup Serial 59G9RC87		lect network connection mode.	0
		W/EI SSID		WiFi	
C	Fi-3704	SmartWiFi	٥	SIM (Advance)	
		Security Auto		Ethernet (Auto)	
equires a type (not auto	* If network is hidden, it re	1.00000	0	Ethernet (Advance)	
C	d	Password		Bluetooth	
nember Encryptio	🗌 Rem				
network	Switch another WiFi				

- 1.4 הכנס את הבקר למצב "התקנה" (בדוק במדריך הבקר, שונה מסוג לסוג).
- 1.5 אשר שהשם של הרשת אליה תרצה להתחבר נכון, הכנס את הסיסמה לרשת ולאחר מכן לחץ על המשך "Next Step".
 - ,WIFI לחץ על "Connect to Device WiFi" לחיבור הבקר לסמארטפון ע"י 1.6 תועבר אוטומטית לדף בחירת רשת WIFI בסמארטפון.

מצא את הבקר(Ubibot-xxx)) והתחבר אליו, לאחר מכן חזור לאפליקציה. 1.7 לחץ על "Start Connecting". המכשיר יתחבר לו WIFI ויצור קשר ראשוני עם 1.8 השרת. לבסוף תתקבל הודעה על הצלחת החיבור או במקרה של תקלה ,הודעת תקלה.

<mark>ر ا</mark> ار	10:57 ◀ UbiBot	al 💌	10:58 🕇	خ ااי
Device X	Settings Wi-Fi		< Add/Set	up Device
TR These are to serve	Wi-Fi			-
the network called turn to the app and	Ubibot-59G9R Unsecured Network	হ 🚺	0	
the next step.	MY NETWORKS		9	RP
1.00	SmartWiFi-3704	a 🗢 j		
	work-GN	a 🗢 i		-
•	OTHER NETWORKS		The device has succes se	sfully registered with rver.
*	jcqxzs	a 🗟 🛈	FI	inish
*	WX7Daysinn	A 🗟 🚺		
e WiFi	姜毅	a 🗟 🗊		
artWiFi-3704	Other			
tched with device r mobile network or				
	Ask to Join Networks	Notify >		
<u>Network</u> SID and displays firm mobile is not	Known networks will be joined aut networks are available, you will be networks.	omatically. If no known notified of available		
'Access-Network' is app.	Auto-Join Hotspot	Ask to Join >		
	Allow this device to automatically	discover nearby		



.2 מסך הבית

היכנס לאפליקציית יוביבוט, כאן תוכל לראות את כל הבקרים הקשורים לחשבון, תוכל לצפו בנתונים האחרונים הנאספו ע"י הבקר. לחץ על כפתור "menu bar" בפינה הימינית התחתונה על מנת לשנות את סדר ההצגה.



תוכל לרענן את הדף ולעבור למצב מפה. מיקום הבקר יוצג לפי כתובת ה IP ולכן אינו מדוייק כמו GPS. תוכל לשנות את מיקום הבקר באופן ידני ע"י הוספת קווי רוחב/אורך ב"הגדרות" בכל בקר.



.3 **ניהול קבוצה**

לחץ על" "My Groups , כאן תוכל לראות את כל הקבוצות שהקמת. לחיצה על "+" להקמת קבוצה חדשה.



לחץ על "+" כשאתה נמצא בקבוצה על מנת להוסיף בקר.



4. הגדרות בקר

תחת עמוד הבקר תראה כמה עמודי משנה. ניתן לדפדף בינהם בעזרת החצים.



4.1 עמוד גרפים

בעמוד הגרפים תוכל לראות את הנתונים שנאספו בגרף. לחץ על כפתור "arrow" להגדרת הגרף בתפריט הנפתח.



4.2

בעמוד זה ניתן לצפות בנתונים הבסיסיים של הבקר. תוכל לשנות את האייקון והשם שלו, בנוסף תוכל למחוק את הנתונים שנאספו או למחוק את הבקר מהמערכת.

17:23		ul 🗢 🗖	1	7:23			ul 🗟 🛙	
	L-GS1		<		L-	GS1		
Charts Info	Rules	Settin >	<	Charts	Info	Rules	Settin	
Channel ID: 7661 Serial No:: 59G9**7CS1 Product ID: ubibot-gs1-a		N S O I I N	letwork Usag torage Used: Th onsumed on the uploads data to etwork Usage: T	ge e amount of platform. Ev the platform 'he total amo	1.3 N storage your di ery time your d . You get 200h iunt of data you	IB / 1.0 GE evice has evice syncs, IB for free.	3	
Channel Name		L-GS1 >	Au Au	our data on the a reb). You get 1GE	app or acces 3 for free.	s the IoT Platfo	rm from the	
Package	nu	ibibot_free	C	hannel Loca	tion 37.3	3954°N -12	2.2478°E	
Storage Usage	5.1 MB /	200.0 MB	it in	is manually loca the device.	ited and ther	e is no position	ing module	
Network Usage	1.3 N	/IB / 1.0 GB			David	a bac boon	activated	
torage Used: The amoun onsumed on the platform	t of storage your d . Every time your d	evice has fevice syncs,	А	ctivated	Devic	(a m	ionth ago)
uploads data to the plat letwork Usage: The total p or from the Platform (e.	form. You get 2008 amount of data you g. when you sync o	dB for free. u have sent data, access	F	irmware			gs1_v1.0.	1
our data on the app or ac veb). You get 1GB for free	cess the loT Platfo	irm from the	V	ViFi SSID			work-GN	J
Channel Location	37.3954°N -12	2.2478°E >	S	IM Card				
is manually located and the device.	there is no positior	ning module	C	reated		10/10/2019	9 14:49:28	3
Activated [®] De	evice has been	activated.	L	ast Sync		14 m	inutes ago	5
	(a n	ionur ago)		Clear Data		Delete C	hannel	ļ

4.3 הגדרת התרעות

לחץ על "Rules" למעבר לעמוד הגדרת התרעות. מוגדרת התרעת ניתוק כברירת מחדל ומכאן תוכל להוסיף התרעות נוספות ע"י לחיצה על כפתור "+".

17:18		ul 🗢 🗀	17:18	ul 🗢 🛙
			< L-GS	1 / New Rule
Charts	Info Rules	Settin >		
efault			Rule Name	
			Field	
Offline Alert It will b	ert le sent by App notifi	-	Temperature	
ation, Email. [Once y]	e-only Alert, Recove		Criteria	
		-	greater than (>)	
ustom		(+)	Z	
ustom			Value	
When the device [L greater than (>) 5 App notification.]	-GS1]'s Temperatur °C; It will be sent b Once-only Alert]		Alert Type Once-Only Alert Select the way (once or con sensor hit the trooper value.	tinuous) to send alert when the
				Next
Nev Notify w	v Offline Alert hen device is offline			
New Notify when the de	V Sensor Alert avice sensor triggen value.	s specified		
New U Notify when	JSB Down Alert	wn.		

4.4 הגדרות חיישנים

בעמוד זה תוכל להגדיר את תדירות הסנכרון של הבקר עם השרת ולקבוע את תדירות הקריאות של החיישנים.

17:13			'II 🕹 🛙	\rightarrow		17:13			÷ι∥ ≎
	L-G	iS1			<				
(Info	Rules	Settings	Share	>	<	Info	Rules	Settings	Sha
Basic					Ва	isic			
Data Sync Battery Life: v should expect increase the t interval. This network cond If you enable reduction in b	with a data sync in t your batteries to battery life you sho is based on using itilons and with hig the Vibration sens iattery life.	15 M terval of 15 min last 4-6 month ould increase t a device under th performance or you will also	finute(s) nutes you ns. To he sync i deal e batteries. a notice a	>	E Skin N N N	Data Sync attery Life: hould exper- icrease the iterval. This etwork com- you enable aduction in	with a data syr it your batterie battery life you is based on us ditions and with the Vibration s battery life.	1 s to last 4-6 m i should increa- ing a device u n high perform sensor you will	5 Minute (s 5 minutes you nonths. To ise the sync nder ideal ance batterier also notice a
Sensors					Se	ensors			
Temperatu	ire & Humidity	5 N	linute(s)	>	ា	emperati	ure & Humic	dity	5 Minute(s
Voltage (B	attery)	3	Hour(s)	>	1	/oltage (E	Battery)		3 Hour(s
Signal This option ca	an not be disabled				S T	ignal	an not be disa	bled	
Advance							5 M	inutes	
Power Sav	ing		Enabled	>			10 M	linutes	
WiFi Mode		Connect	Directly	>			30 M	linutes	
							Cu	stom	

4.5 שיתוף נתונים מבקר

פיצ'ר זה מאפשר שיתוף של משתמש שיוכל לצפות בנתונים ולהוריד אותם. המשתמש איתו שיתפת את הנתונים לא יוכל לשנות הגדרות בבקר, אך כן יוכל לקבל התרעות.

4.5.1

1. המשתמש איתו תרצה לשתף את הנתונים יצטרך להוריד את האפליקציה ולפתוח חשבון.

2. כנס לעמוד הבקר, לחץ על כפתור "share" , לאחר מכן לחץ על "+" והכנס את שם המשתמש או כתובת האימייל של המשתמש לשיתוף.



4.5.2 צפייה בבקרים אחרים- בעמוד הבית לחץ על "Shared Channels", כאן תוכל לראות את הבקרים אותם שיתפו איתך.

16:45		ul 🗢 🗈	16:50	.ıl ≎ I.
	All Channels	۲	<	C-7128
ls M	My Groups Shared	Channels >	< Charts	Info Rules Settin
earch by nan	ne/serial/ID		11/06/2	Temperature °C 2019 17:04:20 - 11/08/2019 16:48:30
-7128	 24.9^{°C} ▲ 35[∞] 5[∨] 〒 -45 267.7^{°C} 248.6^{°C} 		30 27.5 25 22.5	Max.: 27.376595 *C
	₩		20 17.5 11/07/201	Min.: 19.990463 °C
			45	Humidity % 2019 17:04:20 - 11/08/2019 16:48:30
			40	Max.: 37 9
			35 30	بې کې د مېرو کې د د د د کې د مېرو کې د د د د د کې د د کې د د کې د کې د Min: 26 % د مېرو کې د کې د د کې د کې د کې
			25 11/07/2019	12:00 11/08/2019 12:00
*	a a 4		11/06/2	Light Ix 2019 17:04:20 - 11/08/2019 16:48:30
Home S	Setup Inbox Discov	very Me	TUK	Max.: 7211.52002 I

4.6 יומן נתונים

לחץ על חוצץ "Log" על מנת לצפות ביומן הנתונים של הבקר, כאן תוכל לראות האם ההתרעות נשלחו בצורה תקינה.



5. עמוד ההודעות הנכנסות

בחוצץ ההודעות הנכנסות תוכל לראות את כל ההודעות שנשלחו ע"י הבקר. לחץ על כפתור לפתיחת תפריט אפשרויות הסינון.

Inbox 🥩	Inbox 🤘
All	All
☑ Device L-GS1 is back online	
Device L-GS1 is back online and sending new data correctly	All
10/23/2019 15:24:03	Device Related
Device L-GS1 appears to be offline more th	
Device L-GS1 appears to be offline. Last data sync was 1 ho	Alerts
10/23/2019 15:09:01	Accounts
Account information updated - password	Accounts
You have updated your account password. If you didn't mak	News
10/14/2019 11:04:26	
Device L-GS1 has triggered an alert	Device L-GS1 has triggered an alert
Device L-GS1 has triggered an alert (R-13241). Trigger cond	Device L-GS1 has triggered an alert (R-13241). Trigger cond
10/11/2019 17:50:34	10/11/2019 17:50
Device L-GS1 has triggered an alert	Device L-GS1 has triggered an alert
Device L-GS1 has triggered an alert (R-13241). Trigger cond	Device L-GS1 has triggered an alert (R-13241). Trigger con-
10/11/2019 16:35:34	10/11/2019 16:35
Device 59G9***7GS1 Activation Successful	Device 59G9***7GS1 Activation Successful
Your device (Serial 59G9***7GS1) has successfully been reg	Your device (Serial 59G9***7GS1) has successfully been re-
10/10/2019 14:50:17	10/10/2019 14:50
Load More	Load More